

HP9000VE/M, N, CSA HP9000VE/M, N

REF #	DESCRIPTION	PART #	/M QTY	/N QTY		
1	100	ENGINE - B&S 303447-0342	15456-000	1	1	1
2	112	BRACKET, CONSERVER	15270-000	1	1	2
3	114	LEVER, CONSERVER	15291-000	1	1	3
4	115	CLAMP, CONSERVER LEVER	62309-000	1	1	4
5	116	SPARK ARRESTOR GROUP	64159-000	1	1	5
6						6
7	200	AC PANEL ASSY-HP9000/M	15457-000	1	1	7
8	X	PANEL ASSY- CSA HP9000/M	15457-001	X	X	8
9	201	FRONT PANEL (BARE)	15458-000	1	1	9
10	202	LOWER BAFFLE PANEL (BARE)	15223-000	1	1	10
11						11
12	216	BATTERY CABLE - POS (+)	15296-002	1	1	12
13	217	BATTERY CABLE - NEG (-)	15296-001	1	1	13
14						14
15	231	ELECTRO-MAGNET, CONSERVER	15182-000	1	1	15
16	232	CONSERVER MODULE	15110-000	1	1	16
17						17
18	233	RESISTOR, CONS. 250/25W	80132-003	1	1	18
19	234	TRANSFORMER, CONSERVER	63104-000	1	1	19
20	235	SWITCH, CONSERVER-SPST	64089-000	1	1	20
21						21
22	245	RECEPT. - 240V L6-20R	56281-000	1	1	22
23	246	RECEPT. - 120V 5-50R	54545-000	1	1	23
24	247	RECEPT. - 120V L5-30R	56359-000	1	1	24
25	248	RECEPT. - 240V 6-20R	56279-000	2	2	25
26						26
27	249	GFCI RECEPT.- 120V 5-15R	15147-000	2	2	27
28	250	RECEPT. - 240V 6-50R	57325-000	1	1	28
29	251	RECEPT.- 120/240V CS6369	91889-000	1	1	29
30						30
31	258	CIRCUIT BREAKER - 20A 1P	64230-001	2	2	31
32	259	CIRCUIT BREAKER - 20A 2P	57030-001	1	1	32
33	260	CIRCUIT BREAKER - 30A 1P	91977-005	1	1	33
34						34
35	261	CIRCUIT BREAKER - 45A 1P	91977-006	1	1	35
36	262	CIRCUIT BREAKER - 35A 2P	57030-003	1	1	36
37						37
38	280	CAPACITOR (40mfd/370V)	15051-000	3	3	38
39	290	END COVER ASSY	15089-000	1	1	39
40	291	END COVER (BARE)	15085-000	1	1	40
41						41
42	502	ROTOR THRU-BOLT (5/16-24)	23197-028	1	1	42
43	511	END BRACKET - ENG END	15008-001	1	1	43
44	512	*END BRACKET - BRG END**	15156-002	1	1	44
45		*STEEL SHIM - BRG BKT	15688-000	1	1	45
46		*TOLERANCE RING - BRG BKT	15122-003	1	1	46
47						47
48	513	STATOR THRU-BOLT (1/4-20)	15068-010	4	4	48
49	514	STATOR ASSEMBLY- 9000/	15091-008	1	1	49

HP9000VE/M, N, CSA HP9000VE/M, N

REF #	DESCRIPTION	PART #	/M QTY	/N QTY		
50	530	*ROTOR ASSY W/BRG & FAN	15045-009	1	1	50
51	532	*BEARING	50215-000	1	1	51
52						52
53	601	CRADLE	15213-000	1	1	53
54	602	GENERATOR SUPPORT BKT.	15084-000	1	1	54
55	603	SHOCK MOUNT	64062-000	6	6	55
56	610	UNIT TOP COVER, FORMED	15227-001	1	1	56
57						57
58	811	REAR TANK SUPPORT PANEL	15214-000	1	1	58
59	815	FUEL VALVE	64091-000	1	1	59
60	817	FUEL TANK- 4.5 GALLON	64024-000	1	1	60
61						61
62	820	FUEL CAP/GAUGE	62396-003	1	1	62
63	821	BATTERY RACK KIT	15295-000	1	1	63
64	825	END BAFFLE, F. TANK	15144-000	1	1	64
65	831	FOAM STRIP- 0.8" X 3ft	64101-000	1	1	65
66						66
67	901	DECAL SET - WARNING	15209-000	1	1	67
68	902	DECAL - HP9000	64214-016	1	1	68
69	903 X	CSA PARTS (DECALS) -X	15205-100	X	X	69
70	906	NAMEPLATE	63966-000	1	1	70
71	998	OPERATORS MANUAL	60706-087	1	1	71
72		REPAIR PARTS LIST	60701-087	1	1	72
73						73
74		X CSA PARTS ON CSA PREFIX MODELS ONLY				74

-> * This part may be different on your unit. It has been changed to improve the product performance or reliability.

->** Alternate bracket PN 15533-001 (TF/HPM6000)

TECHINICAL DATA

UNIT MODEL SERIES HP9000/M, N

AC RESIDUAL VOLTS 7.0 VAC L-L

FIELD RESISTANCE 0.73 OHMS

WINDING SPEC. (SS#) 1538

ARM. CONNECTION (AC#) 367

FOLLOWING INFORMATION IS FOR REFERENCE ONLY

000	COMPLETE UNIT -HP9000VE/M	15455-001	--	--	000
	COMPLETE UNIT -HP9000VE/N	15455-004	--	--	
111	CONSERVER PLUG/CORD ASSY	15110-001	1	1	111
500	GEN. ASSY. - COMPLETE	15041-017	1	1	500
535	FAN	15136-002	1	1	535
566	RECTIFIER - STD POLARITY	15255-001	1	1	566
567	RECTIFIER - REV POLARITY	15255-002	1	1	567