




GENERATOR EXPERTS

WINCO GENERATORS

 An American Company

225 S. Cordova Ave • Le Center, MN 56057

www.wincogen.com

An American Company

We produce our products in our 200,000ft² facility located in Le Center, Minnesota, equipped with modern engineering, fabrication and assembly capabilities.



Why WINCO

We have partnered with engine manufacturers that specialize in heavy duty, industrial engines. Combining that with industrial generators, plus our generator expertise, creates a durable standby generator you can depend on.



Distributed By:

L-1028/D

WINCO GENERATORS

 An American Company



AIR-COOLED STANDBY GENERATORS

SPECIFICATIONS

MODEL	PSS8B2W	PSS12H2W	PSS20B2W
ELECTRICAL SPECIFICATIONS			
Voltage	120/240 1-PH	120/240 1-PH	120/240 1-PH
LP			
Watts	8,400	12,000	17,000
KVA	8.4	12	17
Amps	35	50	71
NG			
Watts	7,600	10,000	15,000
KVA	7.6	10	15
AMPS	32	41	62
CB Amps	35	50	80
Motor Starting ⁽¹⁾	3 hp	4 hp	5 hp
ENGINE DATA			
Make/Model	B&S Vanguard	Honda GX690	B&S Vanguard
Displacement	570cc	688cc	993cc
Low Oil Protection	Standard	Standard	Standard
dba Rating @ 7M	66	66.8	76
FUEL CONSUMPTION			
LP Vapor	1.6 gal/hr	2.1 gal/hr	3.61 gal/hr
Natural Gas	132 ft³/hr	190 ft³/hr	328 ft³/hr

NOTE: (1) Code G capacitor start motor



OPTIONAL ACCESSORIES

Oil Heater Kit

- Keeps oil warm in frigid climates for easier starts and minimizes engine wear. Recommended for the PSS20.



Factory Installed Off Grid Package

- Available for PSS8 and PSS12
- 12V solar panel and externally mounted receptacles



Battery Heater

- Keeps battery warm for maximum power output at start-up and reduces condensation



Battery

- Interstate Batteries, a company known for their top-quality products since 1952



Maintenance Kit

- Premium synthetic 5W-30 oil
- Spark plug
- Air filter.



Fuel Strainer

- Keeps fuel line free of debris



Automatic Transfer Switch

- Asco 185 and 300 Series

